

# C3A

**EZVIZ C3A IS A FULL HD WI-FI BATTERY CAMERA WITH NIGHT VISION, MICROPHONE AND SPEAKER, SD CARD SLOT, PIR MOTION DETECTION, AND MORE.**

The EZVIZ C3A smart Wi-Fi camera is 100% wire-free camera that it looks sleeker and can help you to cover any angle. Its Weatherproof and rugged features provide maximum performance year round, both indoors and outdoors. With embeded SD card slot in C3A camera, you can record up to 128GB . If you choose EZVIZ W2D battery camera base station, you can control 6 C3A cameras togther, and effectively prolong the battery life of the C3A.



# HIGHLIGHTS



## Fully Wireless

Battery inside the camera and connect to the network by Wi-Fi.



## IP65 rating

Dustproof and Waterproof, Designed For All Weather



## Rechargeable Bigger Battery

5500 mAh Rechargeable lithium battery.



## Microphone and Speaker:

Two-Way Audio Easily



## Intelligent PIR sensor inside:

Only detect motion of the pets and human, Avoid False Alarm



## Two Ways to Save Your Recordings

SD Card and Cloud Storage (Coming Soon)



## Provide A Wider view

The 126° viewing angle allows you to get a wide view of the room/Garden.



## All in one EZVIZ APP

View Anytime, Anywhere with the EZVIZ App



## 7.5m night vision

See what's happening, even in the dark



## Installation Easily

All necessary accessories in the package.

## ABOUT EZVIZ

EZVIZ helps you to app your life. Right from the palm of your hand, you connect visually to your home or your work. Welcome to the smart home and business!

# FEATURES



## FULLY WIRELESS SOLUTION

The EZVIZ C3A is an outdoor standalone 100% wire-free, battery-powered security camera. It enables the user to effortlessly and seamlessly place it anywhere without any hassles of dealing with cables.

## RECHARGEABLE BIGGER BATTERY

5500 mAh Rechargeable lithium battery. A fully charged C3A camera can perform up to 3 months, providing constant protection and minimizing camera downtime. And even working with EZVIZ W2D base station can effectively prolong the battery life of the C3A for up to 9 months. (Work Condition: Normal temperature and environment, Triggered 5min/Day)

## TWO WAYS TO INSTALL

There will be two ways to install the EZVIZ C3A camera. You can either choose the normal way to install the camera with the base included in the package or to use the bracket. (please note the bracket is not included in the package and should be bought separately).

## BUILT-IN INTELLIGENT PIR SENSOR

To avoid false alarms of expected objects movements, EZVIZ C3A is integrated by PIR sensor. Only the motion of pets and human will trigger the PIR sensor, and allow the camera to record footages.

## A WIDER VIEW

The FOV of C3A is 126°. This viewing angle allows you to get a wide view of the room/Garden. You can ensure that everything is under control and covered.



# FEATURES



## See What's happening in the Dark

Even in total darkness you see what's happening. The camera automatically switches to night vision when it's dark. And the range is up to 7.5 metres. You can watch over your baby's sleep without making any noise or check your store or office during the night.



## DUSTPROOF AND WATERPROOF, DESIGNED FOR ALL WEATHER

The C3A has an IP65 rating. This means it is dustproof, waterproof and designed to function in the most extreme circumstances or temperatures, from -25°C to 45°C.



## TWO-WAY AUDIO

Thanks to the built-in two-way audio, you will not be a mere observer but you are able to interact. Just open the EZVIZ app, start the communication and decide whether you want to scare off an intruder or talk with the visitor at your entrance.



## TWO WAYS TO SAVE YOUR RECORDINGS

The EZVIZ C3A supports MicroSD card up to 128GB. Every single C3A is a independent unit to record and save footages. There will be also an optional cloud storage plan soon, EZVIZ aims at ensuring all videos are securely saved.



## All in one EZVIZ APP

With the easy-to-use EZVIZ iOS or Android app, you can view up to four live video streams at the same time. If you want to connect other EZVIZ security devices, such as cameras, sensors, or recorders, you just add them and start using them, all from one and the same app. Its clean layout makes it easy to find all your cameras, change settings and see what's happening with just a few taps.



# SPECIFICATIONS

**Product Name** EZVIZ C3A

## CAMERA

<b>Image sensor</b>	1/4" 2-Megapixel sensor
<b>Lens</b>	2.2mm @ F2.4 /Diagonal FOV: 126°
<b>Night Vision</b>	Up to 25 feet (7.5m)

## Video Parameters

<b>Compression</b>	Standard Smart H.264
<b>Max. Resolution</b>	1920 × 1080, FHD
<b>Frame Rate</b>	50Hz @ 25fps, 60Hz @ 30fps Adaptive frame rate of network transmission
<b>General Function</b>	3D DNR, DWDR, BLC

## Audio Parameters

<b>Audio Input</b>	Built-in Omni-direction microphone
<b>Audio Output</b>	Built-in loudspeaker
<b>Audio Quality</b>	Noise suppression and echo cancellation

## Network

<b>Wireless</b>	Built-in 2.4GHz Wi-Fi and 868MHz radio frequency
<b>Network Configuration</b>	AP mode

## Event

<b>Sensor</b>	PIR Motion Sensor
<b>Alarm</b>	Customized Alert Area
<b>Working Mechanism</b>	Camera will wake up when PIR sensor, live view or playback signal are triggered.

## General

<b>Working Condition</b>	-20°C ~ 45°C, Humidity 95% or less (non-condensing)
<b>Ingress Protection</b>	Grade IP65 weatherproof
<b>Local Storage</b>	One SD card slot on the camera, support Micro SD card memory minimum 8GB, maximum 128G. Recommendation compatibility class 10 or above (SD card is only for camera video storage, 1080p resolution camera's 24 hours recording is approximate 21G)
<b>Built-in Battery</b>	Built-in 5500mAh Rechargeable Li-ion battery
<b>Power Supply Input:</b>	AC 100V–240V~50/60Hz
<b>Output:</b>	DC 5V/1.5A
<b>Power Cable Length:</b>	1.5m
<b>Power Cable Out put Interface Type:</b>	Micro-B
<b>Standby Wi-Fi power Consumption:</b>	≤ 8mW

## What's in the box?

- 1x EZVIZ camera C3A
- 1x Battery
- 1x Magatic Mount
- 1x Screw Kit
- 1x USB Cable
- 10x Power Adapter
- 1x Quick Start Guide